

Centurion

EXPLOSION PROOF TECHNICAL DATA SHEET

Rescue Hand Lamp Charger Unit

Model : LC-333

Factory Code : 792272

HS Code : 8504319000



Technical Details:

Apparatus Standards : 2014/35/EU LVD Directive,
2014/30/EU EMC Directive

Enclosure : Polypropylene

Input Voltage : AC 90-260V 50/60Hz

Power consumption : 50W

Output : DC 12V, Max 2A x 2

Recharge Time : 1.5hrs

Ingress Protection : IP20

Compatible hand lamp : EX-2380

Weight : 0.600 Kg

Packing : 12pcs/carton, size : 47*47*32cm

This hand lamp charger is compatible with the product of EX-2380. Batteries are charged internally. In this product which passes through the charging stud on the base of the hand lamp. The charger is designed to hold the torch while charging, using the "snap in / snap out"function, quickly releases, but remains fixed so that they can always ready to use. It contains two charging ports to allow both hand lamp to be charged simultaneously.

The LC-333 charger is for suitable for 90 volts to 260 volts wide voltage and the voltage will automatically proceed switch, while charging to detect the input voltage. And European 2-pin plug and US 2-pin plug adapter are supplied for worldwide used.